

Bench Digital Multimeter

True RMS, 4-1/2 Digit, LED Display

- Can read measurement data with high speed and accuracy
- All measuring ranges have circuit protection
- 0.03% DCV accuracy
- **DC Volts:** 10 μ V ~1200V, 5 ranges
- **AC Volts:** 10mV ~1000Vac, 5 ranges
- **AC/DC Current:** 200A to 20A, 5 ranges
- **Resistance:** 10mohm - 20Mohm
- **Dimensions/Weight:** 216(W) x 83(H) x 29(L) mm; 4Kg (8.8 lbs)

